



AJAX

Smoke, heat and co fire detector

FIREPROTECT2-HSC-RB-W

TECHNICAL SPECIFICATIONS

| | |
|------------------------|---|
| Compatibility | Hub Plus/Hub 2/Hub 2 Plus/Hub Hybrid |
| LED indicators | Yes |
| LED colors | Verde / Rojo / Amarillo |
| Tamper | Yes |
| Tipo de notificación | Acoustics |
| Siren Volume | 85dB to 3 meter |
| Temperature activation | 64°C |

AMBIENT

| | |
|-----------------------|---------------------|
| Operating temperature | 0 °C ~ 50 °C |
| Degree of protection | IP20 |
| Use | Indoor |
| Maximum humidity | 80% |

VIA RADIO

| | |
|-----------------------|---|
| Frequency | 868.0 MHz ~ 868.6 MHz |
| Transmission distance | Up to 1700 m (without obstacles) |
| Maximum power RF | Hasta 20 mW |
| Protocol | Jeweller |

SENSOR

| | |
|----------------|---|
| Type of sensor | Detección de humo: sensor óptico de doble espectro / Detección de temperatura: termistor / Detección de CO: sensor químico |
|----------------|---|

DETECTION

| | |
|---------------|---------------------------|
| Detector type | Smoke, heat and CO |
|---------------|---------------------------|

MATERIAL AND DIMENSIONS

| | |
|-----------------------|--------------------------|
| Dimensions | 124 x 124 x 45 mm |
| Net weight | 270 g |
| Weight with packaging | 330 g |
| Color | White |

GENERAL INFORMATION

| | |
|------------|----------------------|
| Technology | Wireless |
| Type | Fire detector |

POWER CONSUMPTION

| | |
|------------------|------------------------|
| Battery model | 2 x CR123A / 3V |
| Battery duration | Up to 7 años |

DETECCIÓN (INCENDIO)

| | |
|--------------------|-------------------|
| Termovelocimétrico | 10°C / min |
|--------------------|-------------------|

